


RSK SERIES

Direct Burial Splice Kits with Rubber Covers

RECOMMENDED INSTALLATION INSTRUCTIONS

1. Select correct cut-off ring for cable being used. Cut insulating sleeve and cap so that cable size desired is left showing.



2. Bevel or pencil cable insulation to ease insulation. See chart below for strip length and apply silicone grease to cut openings.



3. Apply silicone grease to cut openings on sleeve and cap. Slide them over the cable ends as shown.

4. Install splice connector. Use torque chart below for proper specs.

5. Apply silicone grease to sleeve opening. Slide sleeve and cap* together, centering the housing over the spliced connection.



* To accommodate some splices, it may be necessary to remove the hard grey liner in the cap.


KIT TYPE	WIRE SIZE	WIRE STRIP LENGTH	TIGHTENING TORQUE IN IN. LBS
RSK-2/0	#14 - #10	1/4"	35
	#8		40
	#6 - #4		45
	#3 - 2/0 AWG		50
RSK-350	#6 - #4 #2 - 350 AWG	3/4"	120
			240
RSK-500	2/0 AWG - 350 MCM 400 - 500 MCM	2 1/4"	240
			360
RSK-750	250 - 350 MCM 400 - 750 MCM	3 1/4"	240
			360

RSK SERIES

Direct Burial Splice Kits with Rubber Covers

RECOMMENDED INSTALLATION INSTRUCTIONS

1. Select correct cut-off ring for cable being used. Cut insulating sleeve and cap so that cable size desired is left showing.



2. Bevel or pencil cable insulation to ease insulation. See chart below for strip length and apply silicone grease to cut openings.



3. Apply silicone grease to cut openings on sleeve and cap. Slide them over the cable ends as shown.

4. Install splice connector. Use torque chart below for proper specs.

5. Apply silicone grease to sleeve opening. Slide sleeve and cap* together, centering the housing over the spliced connection.



* To accommodate some splices, it may be necessary to remove the hard grey liner in the cap.

KIT TYPE	WIRE SIZE	WIRE STRIP LENGTH	TIGHTENING TORQUE IN IN. LBS
RSK-2/0	#14 - #10	1/4"	35
	#8		40
	#6 - #4		45
	#3 - 2/0 AWG		50
RSK-350	#6 - #4 #2 - 350 AWG	3/4"	120
			240
RSK-500	2/0 AWG - 350 MCM 400 - 500 MCM	2 1/4"	240
			360
RSK-750	250 - 350 MCM 400 - 750 MCM	3 1/4"	240
			360