

Enterprise 1300

SKU: 460049 / 460050

FEATURES

- Three outdoor antenna ports to target multiple carrier towers.
- Wired or LTE WilsonPro Cloud access for remote functionality.
- Up to 26 dBm in uplink power and 17 dBm in downlink power.
- XDR technology to virtually eliminate shutdown or signal loss.
- 4.3-inch LCD touchscreen for an enhanced user-experience.
- Works with ALL phones and cellular devices on ALL carriers.



WALL MOUNT OPTION
(Enterprise 1300R)

Kit Includes



Outside Directional Antenna (314411)



Inside Dome Antenna x4 (304412)



Lightning Surge Protector (859902)



2 ft. Wilson400 Cable (952302)



100ft Low-Loss Wilson400 Cable x5 (952300)



Wilson 1/2-Inch Plenum Cable 500 ft Spool (952003)



Connector for 1/2 inch Plenum Cable, 10-pack (970014-10)

About

The WilsonPro **Enterprise 1300/1300R** is a commercial-grade, in-building cellular amplifier that represents the latest in cell signal boosting technology—including a revolutionary industry-first, three outdoor-antenna-port configuration. Depending on cell tower locations, using up to three outdoor antennas (each dedicated to a specific frequency band to collectively amplify signals from multiple towers) helps maximize coverage in commercial spaces up to 40,000 sq. ft.*

Based on user need or preference, the Enterprise 1300/1300R can also utilize “common mode” as a default; using only a single outdoor (donor) antenna and a single port to receive cell signal.

With wired or LTE access (using the built-in cellular modem) to the WilsonPro Cloud for remote functionality, the Enterprise 1300/1300R provides integrators and building managers with the capability to remotely manage, monitor, and adjust their amplifier, as well as receive real-time updates on a smartphone or tablet. Immediate notification of issues, such as system failure, oscillation, or change in signal strength is also provided via text or email.

The Enterprise 1300/1300R generates up to 26 dBm in uplink power—enabling it to reach towers at much greater distances. With up to 17 dBm in downlink power, it’s also one of the most powerful amplifiers in its price range. The “R” model name signifies its rack-mount option.

This amplifier includes a 3-year manufacturer’s warranty and a 30-day money-back guarantee.

*Depending on outside signal conditions.

Specifications

MODEL NUMBER	460049* / 460050*	
FREQUENCIES	Band 12/17	700 MHz
	Band 13	700 MHz
	Band 5	850 MHz
	Band 4	1700/2100 MHz
	Band 25	1900 MHz
MAX GAIN	70 dB	
MAX UPLINK POWER	26 dBm	
MAX DOWNLINK POWER	17 dBm	
IMPEDANCE	50 Ohm	
POWER	110-240V, 50-60Hz, 60W	
CONNECTORS	N-Female	
AMPLIFIER DIMENSIONS	19 x 12 x 2.5 / 17.5 x 12 x 3.75 in	
AMPLIFIER WEIGHT	16.515 lbs / 9.66 lbs	

⚠ WARNING: This product can expose you to chemicals including Nickel, which is known to the State of California to cause cancer, and Bisphenol A, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Detailed Specifications

SKU	460049 / 460050				
MODEL NUMBER	460049 / 460050				
FCC ID	PWO460049 / PWO460049 / PWO460050 / PWO460050				
CONNECTORS	N-Connectors				
ANTENNA IMPEDANCE	50 Ohms				
FREQUENCY	698-716 MHz, 729-746 MHz, 777-787 MHz, 824-894 MHz, 1850-1990 MHz, 1710-1755/2110-2155 MHz				
POWER OUTPUT FOR SINGLE CELL PHONE (Uplink) dBm	700 MHz Band 12/17 23.9	700 MHz Band 13 23.9	800 MHz 25.1	1700 MHz 23.7	1900 MHz 26.7
POWER OUTPUT FOR SINGLE CELL PHONE (Downlink) dBm	700 MHz Band 12/17 16.7	700 MHz Band 13 16.8	800 MHz 16.9	2100 MHz 16.8	1900 MHz 16.8
NOISE FIGURE	5 dB Nominal				
ISOLATION	>90 dB				
POWER REQUIREMENTS	120V AC 0.5A				

Each Signal Amplifier is individually tested and factory set to ensure FCC compliance. The Signal Amplifier cannot be adjusted without factory reprogramming or disabling the hardware. The Signal Amplifier will amplify, but not alter incoming and outgoing signals in order to increase coverage of authorized frequency bands only. If the Signal Amplifier is not in use for five minutes, it will reduce gain until a signal is detected. If a detected signal is too high in a frequency band, or if the Signal Amplifier detects an oscillation, the Signal Amplifier will automatically turn the power off on that band. For a detected oscillation the Signal Amplifier will automatically resume normal operation after a minimum of 1 minute. After 5 (five) such automatic restarts, any problematic bands are permanently shut off until the Signal Amplifier has been manually restarted by momentarily removing power from the Signal Amplifier. Noise power, gain, and linearity are maintained by the Signal Amplifier's microprocessor.

The Manufacturer's rated output power of this equipment is for single carrier operation. For situations when multiple carrier signals are present, the rating would have to be reduced by 3.5 dB, especially where the output signal is re-radiated and can cause interference to adjacent band users. This power reduction is to be by means of input power or gain reduction and not by an attenuator at the output of the device.

WARNING. This is **NOT** a CONSUMER device. It is designed for installation by FCC LICENSEES and QUALIFIED INSTALLERS. You **MUST** have an FCC LICENSE or express consent of an FCC Licensee to operate this device. Unauthorized use may result in significant forfeiture penalties, including penalties in excess of \$100,000 for each continuing violation.

ASSEMBLED IN THE USA



Kit Variations



ENTERPRISE
1300

SKU 460049

KIT CONTENTS Amp only

PACKAGE L/W/H/WEIGHT 27.38" / 18" / 6.25" / 20.90 lbs
SHIPS IN ONE BOX



ENTERPRISE
1300R

SKU 460050

KIT CONTENTS Amp only

PACKAGE L/W/H/WEIGHT 27.38" / 18" / 6.25" / 13.90 lbs
SHIPS IN ONE BOX



FOR PARTNER'S USE

Support



3 YEAR WARRANTY FROM PURCHASE

US Web: wilsonconnectivity.com

US Phone: +1 800 871 1612

INTL Phone: +44 1223 982031