

# EASY-TWIST®

## WIRE CONNECTORS



**C22-N-B**

**1000 PCS**

TO BE SOLD ONLY WITH INSTALLATION INSTRUCTIONS:

1. Turn off power before installing or removing connectors.
2. Strip wires .51" (13mm) max, .47" (12mm) Min.
3. Twist stripped wires together with ends even & enter into connector.
4. Center the crimp tool die around the sleeve.

Use Hand Tool: Lobster AK-25

**FOR USE WITH COPPER TO COPPER**

Temperature Rating: 105° C (221° F) Max  
Voltage Rating: 300V Max

### WIRE COMBINATIONS:

Listed as pressure-type wire connector on the following stranded and/or solid wire combinations.

#### For UL Listed

Voltage Rating 300V Max:

2 x 22	22 + 18
3 x 22	2 x 22 + 20
2 x 20	2 x 22 + 18
3 x 20	20 + 18
2 x 18	2 x 20 + 22
22 + 20	2 x 20 + 18
22 + 20 + 18	



- ⚠ **WARNING:** Cancer and reproductive harm
  - ⚠ **ADVERTENCIA:** Cáncer y daño reproductivo
  - ⚠ **ADVERTISSEMENT:** Cancer et troubles de l'appareil reproducteur
- [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

MADE IN CHINA



NSI Industries  
800.321.5847  
[nsiindustries.com](http://nsiindustries.com)



6 62381 06854 5

NSI Industries, LLC  
EASY TWIST BAG LABEL

# C22-N-B

CE1

1/0 (BLACK)

03/2024

do NOT print - for placement only