

# TPX100/TPX100S Low Voltage Pool and Spa Transformer

LOW VOLTAGE TRANSFORMER DESIGNED TO SUPPLY 12VAC, 13VAC TO UNDERWATER POOL AND SPA LIGHTS

# **APPLICATIONS**

- Led pool and spa lights
- Submersible fixtures
- Landscape lighting
- Decorative lighting
- Garden Lights

#### **FEATURES**

- Built-in circuit protection will disconnect power to the transformer in case of defect or overload
- Meets NEC Article 680.23 and any applicable local codes

## **SPECIFICATIONS**

- Voltage: 120VAC; 60Hz
- Output: 12V, 13V
- Watts: 100₩
- Exiting Current: W/ no load Max 150mA W/full load - Max 1250mA
- Operating Temperature: 14°F to 113°F (-10°C to 45°C).
- Storage Temperature: -4°F to 140°F (-20°C to 60°C).
- Temperature Rise: 80°C w/ max current and voltage and respects to an ambient temp. of 25°C
- Knockouts: <sup>1</sup>/<sub>2</sub>" and <sup>3</sup>/<sub>4</sub>"
- TPX100 Material: Cold Rolled Steel with Powder Coat Finish
- TPX100S Material: Stainless Steel

## **REGULATORY LISTINGS**

cCSAus

#### LIMITED WARRANTY

• 1- year manufacturer's warranty

Project Info:	Туре:
Job Ref:	Catalog Number:
Approvals:	Date:
Item Number:	UPC Code:








### TPX100 / TPX100S

## DIMENSIONS



#### WIRING DIAGRAM

